


# IGDW..F400 – Bushing-type Current Transformer

The IGDW..F400 is used for measurement and protection in applications. The cast resin insulated indoor bushing-type current transformer can be used up to 24 kV. The current transformer is maintenance-free and mountable in any position.



## **Ordering Specifications**

For the customized design of your ELEQ IGDW..F400 Current Transformer the following information is required:


#### Mandatory

- Rated primary current
- Rated secondary current
- Rated output
- Accuracy class
- Frequency

#### **Optional**

Other relevant requirements

# Wiring diagram IEC 61869-2



### **Technical specifications**

•	
Environmental conditions	
This product is designed to be safe	
under the following conditions:	
Location:	Indoor use
Ambient air temperature:	-5°C +40°C; other
0	temperatures on request
' '	-25°C +50°C
•	5% 95%, non condensing
Altitude:	Max. 1000m above NN; at
Protection degree (secondary	>1000m data required
ŭ ,	IP20
	11 20
• • •	150 04000 04555 0 55 40
	IEC 61869-2/IEEE C 57.13; etc.
•	400 1 14
` '	100 x ln/1s
• • • • • • • • • • • • • • • • • • • •	2,5 x lth
` '	up to 200%
	24/50/125kV
•	50/60Hz
	E
	5A – 5000A
Rated secondary current:	1A or 5A; other options available
Detect cutout	on request As required.
Nateu output.	'
Accuracy class:	For example 2,5VA, 10VA, 30VA As required.
nocuracy class.	·
Secondary terminal:	For example 0,2S, 5P10
occordary terrifical.	Screw terminals M5 (max. 2.5Nm)
	This product is designed to be safe under the following conditions: Location:

### **Dimensions**

